

15 KV
COOPER

CONNECTOR #2 AWG
COOPER CC6A11U

2.72" [2 3/4"]

9.77" [9 3/4"]

3-4 PRE-SWAGE (IA)
INJECTION ADAPTER

INSULATION CUT
BACK TEMPLATE

TOOL STOP

INSULATION
220 MILS

SEMI-CON SHIELD

4.44" [4 7/16"]

6.36" [6 3/8"]

10.77" [10 3/4"]

MARKING TAPE

COOPER® BT625 T-BODY

SEMI-CON SHIELD

CABLE INSULATION
ADAPTER CA625B

TOOL STOP CUT
BACK TEMPLATE

**NOTE: THE INSULATION ADAPTER MUST
BE ON THE CABLE BEFORE SWAGING THE
CONNECTOR. SEE NRI 31 & NRI 32**

The marking tape must be located from end of strip cable (as shown as pre-swage) to end of cable insulation adapter and should be within 1/4" inch [6mm] after swage.

CPR-15 BT625B #2 3-4 5mar10

© Copyright 2007, Novinium, Inc. All rights reserved.

IA is protected by patents and patents pending

COOPER is a registered trademark of Cooper Power Systems. novinium is a registered trademark of novinium.

(Printing instructions: For best results, print in color, protect w/5mil laminate and trim to size.)

SCALE: 1:1

8.5 x 22 paper size

novinium