

25 KV  
COOPER

CONNECTOR 350 AWG  
COOPER CC6A19U

9.77" [9 3/4"]  
2.66" [2 11/16"]

9-6 PRE-SWAGE (IA)  
INJECTION ADAPTER

INSULATION CUT  
BACK TEMPLATE

TOOL STOP

INSULATION  
260 MILS

SEMI-CON SHIELD

4.44" [4 7/16"]

6.30" [6 5/16"]

10.77" [10 3/4"]

COOPER® BT625 T-BODY

MARKING TAPE

SEMI-CON SHIELD

CABLE INSULATION  
ADAPTER CA625-F

TOOL STOP CUT  
BACK TEMPLATE

**NOTE: THE INSULATION ADAPTER MUST  
BE ON THE CABLE BEFORE SWAGING THE  
CONNECTOR. SEE NRI 31 & NRI 32**

The marking tape must be located from end of strip cable (as shown as pre-swage) to end of cable insulation adapter and should be within 1/4" inch [6mm] after swage.

CPR-25 BT625F 350 9-6 5mar10

© Copyright 2007, Novinium, Inc. All rights reserved.  
IA is protected by patents and patents pending  
COOPER is a registered trademark of Cooper Power Systems. novinium is a registered trademark of novinium.  
(Printing instructions: For best results, print in color, protect w/5mil laminate and trim to size.)  
SCALE: 1:1 8.5 x 22 paper size

