

RICHARDS
15KV

CONNECTOR 4/0 AWG
RICHARDS P6AL-12

2.67" [2 11/16"]

6-4 PRE-SWAGE
INJECTION ADAPTER (IA)

TOOL STOP

6.30" [6 5/16"]

10.77" [10 3/4"]

4.45" [4 7/16"]

9.77" [9 3/4"]

**INSULATION CUT
BACK TEMPLATE**

INSULATION
220 MILS

SEMI-CON SHIELD

MARKING TAPE

RICHARDS 62LCN1 or 62LCT1

SEMI-CON SHIELD

CABLE INSULATION ADAPTER
RICHARDS P625CA-H

**TOOL STOP CUT
BACK TEMPLATE**

The marking tape must be located from end of strip cable (as shown as pre-swage) to the end of cable insulation adapter and should be within 1/4 inch [6mm] after swage.

**NOTE, THE INSULATION ADAPTER MUST
BE ON THE CABLE BEFORE SWAGING THE
CONNECTOR. SEE NRI 31 & NRI 32**

RCH-15 62LC(N-T)1-H 40 6-4 26mar10

© Copyright 2007, Novinium, Inc. All rights reserved.
IA is protected by patents and patents pending
RICHARDS is a registered trademark of Richards Mfg. Novinium is a registered trademark of Novinium.
(Printing instructions: For best results, print in color, protect w/5mil laminate and trim to size.)



SCALE: 1:1 8.5 x 22 paper size