

TOOL STOP POSITION TEMPLATE

ELASTIMOLD® 156LR-G
 ELASTIMOLD® 156LR-H
 ELASTIMOLD® 156LR-J

5" TOOL STOP

EMD-25 156LR-G-H-J 1to40 4to7-2or3 6sep12

IA is protected by patents and patents pending.
 © www.novinium.com/patents.aspx
 Elastimold is a registered trademark of I.T.S. Novinium is a registered trademark of Novinium, Inc.
 (Printing instructions: For best results, print in color, protect with W/10 MIL Laminate & trim to size.)
 SCALE: 1:1
 8.5 x 11 paper size

ELASTIMOLD®
25KV
DEADBREAK

SEMI-CON SHIELD

4-2, 5-2, 6-3 or 7-3 PRE-SWAGE
 INJECTION ADAPTER (IA)

INSULATION RANGE
 156LRG 0.845-0.950
 156LRH 0.870-1.050
 156LRJ 1.000-1.145

6⁵/₈" PRE-SWAGE

5⁵/₈"

3¹/₂" POST-SWAGE

6⁷/₈" POST-SWAGE

1³/₈"

COMPRESSION
 CONNECTOR
 1, 1/0, 2/0, 3/0 or 4/0

The final length
 should be within
 1/8" (3mm) of the
 given Post-Swage
 length.

3/4"

1³/₄"

**INSULATION CUT BACK
 TEMPLATE**



novinium
 masters of reliability

