

TOOL STOP POSITION TEMPLATE



eng
chk

ELASTIMOLD® 273-274AELR 7495
ELASTIMOLD® 273-274AELR 88110

5 1/8" TOOL STOP

10" POST-SWAGE

5 15/16" EXPOSED METAL POST SWAGE

The final length should be within 1/8" (3mm) of the given Post-Swage length.

ELASTIMOLD®
25 KV

SEMI-CON SHIELD

INSULATION CUT BACK TEMPLATE

INSULATION RANGE	
273-274 AELR 7495	0.760-0.950
273-274 AELR 88110	0.900-1.100

9 5/8" PRE-SWAGE

6 3/8"

INJECTION ADAPTER (IA)
4-2, 5-2, or 6-2
PRE-SWAGE

SPLICE CONNECTOR,
RICHARDS ALCR9-8-NV #2, #1 x 1/0
RICHARDS ALCR10-9-NV 2/0 x 1/0
RICHARDS SALC9-NV 1/0 x 1/0

1 9/16"

1/0 7-STRAND
COPPER CONDUCTOR

SHORT COPPERTOP,
1/0 AND -2
SWAGE RING

3"
4 1/8"

EXTENSION LENGTH TEMPLATE
CUT TO LENGTH IN FIELD

EMD-25 273or274AELR 1to2o 4to6-2 7apr14

© www.Novinium.com/patents.aspx
IA is protected by patents and patents pending

Elasimold is a registered trademark of T.S.B. Novinium is a registered trademark of Novinium, Inc.
(Printing instructions: For best results, print in color, protect w/10 MIL laminate and trim to size.)

SCALE: 1:1
8.5 x 14 paper size